

DATA ARTIKEL ILMIAH

Judul	: An Adaptive Internal Model for Load Frequency Control Using Extreme Learning Machine
Penulis	: Adelhard Beni Rehiara, He Chongkai, Yutaka Sasaki, Naoto Yorino, Yoshifumi Zoka
Abstrak	: As an important part of a power system, a load frequency control has to be prepared with a better controller to ensure internal frequency stability. In this paper, an Internal Model Control (IMC) scheme for a Load Frequency Control (LFC) with an adaptive internal model is proposed. The effectiveness of the IMC control has been tested in a three area power system. Results of the simulation show that the proposed IMC with Extreme Learning Machine (ELM) based adaptive model can accurately cover the power system dynamics. Furthermore, the proposed controller can effectively reduce the frequency and mechanical power deviation under disturbances of the power system.
Keywords	: ELM; IMC; LFC; MPC; power system
Nama Jurnal	: TELKOMNIKA (Telecommunication, Computing, Electronics and Control)
Volume/Nomor	: Vol 16, No 6
Edisi	: Desember 2018
Alamat web	: http://journal.uad.ac.id/index.php/TELKOMNIKA/article/view/11553
Kategori	: Jurnal Internasional (Q3)
SJR	: 0.21 (2019)

Accredited by DGHE, Decree No. 51/DIKTI/Kep/2010

ISSN 1693-6930

TELKOMNIKA

Indonesian Journal of Electrical Engineering

Vol. 16, No. 6, December 2018

Published by

Universitas Ahmad Dahlan (UAD), Yogyakarta, Indonesia

and

Institute of Advanced Engineering and Science (IAES)





HOME ABOUT LOGIN REGISTER SEARCH CURRENT ARCHIVES ANNOUNCEMENTS

Home > [About the Journal](#) > **Editorial Team**

Editorial Team

Editor-in-Chief

[Assoc. Prof. Dr. Tole Sutikno](#), Universitas Ahmad Dahlan, Indonesia

Area Editor for Electrical Power Engineering

[Assoc. Prof. Dr. Ahmet Teke](#), Cukurova University, Turkey

Area Editor for Electronics Engineering

[Prof. Ing. Mario Versaci](#), Università degli Studi di Reggio Calabria, Italy

Area Editor for Power Electronics and Drives

[Prof. Dr. Yang Han](#), University of Electronic Science and Technology of China, China

Area Editor for Instrumentation and Control Engineering

[Prof. Dr. Paolo Visconti](#), University of Salento, Italy

Area Editor for Signal, Image and Video Processing

[Prof. Dr. Nidhal Carla Bouaynaya](#), Rowan University, United States

Area Editor for Communication System Engineering

[Prof. Dr. Zahrladha Zakaria](#), Universiti Teknikal Malaysia Melaka, Malaysia

Area Editor for Computer Network and System Engineering

[Assoc. Prof. Dr. Muhammad Nadzir Marsono](#), Universiti Teknologi Malaysia, Malaysia

Area Editor for Computer Science and Information System

[Assoc. Prof. Dr. Wanquan Liu](#), Curtin University of Technology, Australia

Area Editor for Machine Learning, AI and Soft Computing

[Prof. Dr. Luis Paulo Reis](#), Universidade do Porto, Portugal

Area Editor for Internet of Things

[Assoc. Prof. Dr. Chau Yuen](#), Singapore University of Technology and Design, Singapore

Associate Editors

[Prof. Dr. Simon X. Yang](#), University of Guelph, Canada
[Prof. Dr. Ahmad Saadi Samosir](#), Lampung University, Indonesia
[Prof. Dr. Alex Pappachen James](#), Indian Institute of Information Technology and Management-Kerala, India
[Prof. Dr. Antonios Gasteratos](#), Democritus University of Thrace, Greece
[Prof. Dr. Badrul Hisham Ahmad](#), Universiti Teknikal Malaysia Melaka, Malaysia
[Prof. Dr. Chi-Hua Chen](#), Fuzhou University, China
[Prof. Dr. Emilio Jimenez-Macias](#), University of La Rioja, Spain
[Prof. Dr. Francis C. M. Lau](#), Hong Kong Polytechnic University, Hong Kong
[Prof. Franco Frattolillo, Ph.D.](#), University of Sannio, Italy
[Prof. Dr. George A. Papakostas](#), International Hellenic University, Greece
[Prof. Dr. Huchang Liao](#), Sichuan University, China
[Prof. Longquan Yong](#), Shaanxi University of Technology, China
[Prof. Dr. Mahmoud Moghavvemi](#), University of Malaya, Malaysia
[Prof. Ing. Mario Versaci](#), Università degli Studi di Reggio Calabria, Italy
[Prof. Dr. Melchior Pierre](#), University of Bordeaux, France
[Prof. Dr. Pascal Lorenz](#), University of Haute Alsace, France
[Prof. Dr. Qiang Yang](#), Zhejiang University, China
[Prof. Dr. Sanjay Misra](#), Covenant University, Nigeria
[Prof. Dr. Surinder Singh](#), SLIET Longowal, India
[Prof. Dr. Teddy Surya Gunawan](#), International Islamic University of Malaysia, Malaysia
[Prof. Dr. Zhenyu Zhou](#), North China Electric Power University, China
[Prof. Dr. Zita Vale](#), Instituto Politécnico do Porto, Portugal
[Assoc. Prof. Dr. D. Jude Hemanth](#), Karunya University, India
[Assoc. Prof. Dr. Hamed Mojallali](#), The University of Guilan, Iran, Islamic Republic of
[Assoc. Prof. Dr. Imran Sarwar Bajwa](#), Islamia University, Pakistan
[Assoc. Prof. Dr. Jumri Yunas](#), Universiti Kebangsaan Malaysia, Malaysia
[Assoc. Prof. Dr. Peng Zhang](#), University of Connecticut, United States
[Assoc. Prof. Dr. Shahrin Md Ayob](#), Universiti Teknologi Malaysia, Malaysia
[Asst. Prof. Dr. Andrea Francesco Morabito](#), University of Reggio Calabria, Italy
[Asst. Prof. Dr. Domenico Cuzzo](#), University of Naples Federico II, Italy
[Dr. Abdullah M. Ilyasu](#), Tokyo Institute of Technology, Japan
[Dr. Adamu I. Abubakar](#), International Islamic University Malaysia, Malaysia
[Dr. Anh-Huy Phan](#), Skolkovo Institute of Science and Technology (Skoltech), Russian Federation
[Dr. Arafat Al-Dweik](#), Khalifa University, United Arab Emirates
[Dr. Arcangelo Castiglione](#), University of Salerno, Italy
[Dr. Arianna Mencattini](#), University of Rome "Tor Vergata", Italy
[Dr. Athanasios Kakarountas](#), University of Thessaly, Greece
[Dr. Aniello Castiglione](#), University of Naples Parthenope, Italy
[Dr. Grienggrai Rajchakit](#), Maejo University, Thailand
[Dr. Javed Iqbal](#), Sarhad University of Science and Information Technology, Pakistan
[Dr. Khader Shameer](#), Mount Sinai Health System, United States
[Dr. Lai Khin Wee](#), Universiti Malaya, Malaysia
[Asst. Prof. Dr. Makram A. Fakhri](#), University of Technology, Iraq
[Mark S. Hooper](#), IEEE Consultants' Network of Silicon Valley, United States
[Dr. Paolo Crippa](#), Università Politecnica delle Marche, Italy
[Dr. Qammer Hussain Abbasi](#), University of Glasgow, United Kingdom
[Dr. Ramón J. Durán](#), University of Valladolid, Spain
[Dr. Saleem Abdullah](#), Abdul Wali Khan University Mardan, Pakistan
[Dr. Santhanakrishnan V. R. Anand](#), New York Institute of Technology, United States
[Dr. Sudhanshu Tyagi](#), Thapar Institute of Engineering and Technology, India
[Dr. Winai Jaikla](#), King Mongkut's Institute of Technology Ladkrabang, Thailand

Editorial Board Members

[Assoc. Prof. Dr. Tossapon Boongoen](#), Mae Fah Luang University, Thailand
[Prof. Dr. Samir Ladaci](#), Nananal Polytechnic School of Constantine, Algeria
[Assoc. Prof. Dr. Nicola Ivan Giannocaro](#), University of Salento, Italy
[Dr. Imran Shafique Ansari](#), University of Glasgow, United Kingdom
[Prof. Dr. Jia-Chin Lin](#), National Central University, Taiwan
[Prof. Dr. Fateh Krim](#), Ferhat Abbas University of Setif, Algeria
[Assoc. Prof. Dr. Mohd Ashraf Ahmad](#), Universiti Malaysia Pahang, Malaysia
[Dr. Brij Bhooshan Gupta](#), National Institute of Technology Kurukshetra, India



[Dr. Haruna Chiroma](#), National Yunlin University of Science and Technology, Taiwan, Province of China
[Assoc. Prof. Dr. Giovanni Pau](#), Kore University of Enna, Italy
[Assoc. Prof. Dr. Candid Reig](#), University of Valencia, Spain
[Assoc. Prof. Dr. Nik Rumzi Nik Idris](#), Universiti Teknologi Malaysia, Malaysia
[Prof. Dr. Youssef Errami](#), University Chouaib Doukkali, Eljadida, Morocco
[Prof. Dr. Faycal Djeflal](#), University of Batna, Batna, Algeria
[Assoc. Prof. Dr. Jinsong Wu](#), Universidad de Chile, Chile
[Dr. Auzani Jidin](#), Universiti Teknikal Malaysia Melaka, Malaysia
[Assoc. Prof. Dr. Larbi Boubchir](#), University of Paris 8, France
[Prof. Dr. Felix Albu](#), Valahia University of Targoviste, Romania
[Prof. Dr. Tarek Bouktir](#), Ferhat Abbas University, Setif, Algeria
[Dr. Lisandro Lovisolo](#), Universidade do Estado do Rio de Janeiro, Brazil
[Dr. Kamil Dimillier](#), Near East University, Cyprus
[Dr. Harish Chandra Dubey](#), Microsoft Corporation, United States
[Dr. Thi-Lan Le](#), International Research Institute MICA, Viet Nam
[Dr. Georgia Tseliou](#), Panepistimion Patron, Patra, Greece/European Patent Office (EPO), Netherlands
[Dr. Vorapo Patanavijit](#), Assumption University, Thailand
[Dr. Abdulrahman Emhemed](#), Bright Star University, Libya
[Dr. Taghi Javdani Gandomani](#), Shahrekord University, Iran, Islamic Republic of
[Dr. Angelo Trotta](#), University of Bologna, Italy
[Dr. Sushil S. Thale](#), Fr. C. Rodrigues Institute of Technology, India
[Dr. Ying-Khai Tsh](#), San Diego State University, United States
[Prof. Salazar Addison](#), Universidad Politécnica de Valencia, Spain
[Dr. Prasant Kumar Sahu](#), IIT Bhubaneswar, India
[Dr. Thanh D. Nguyen](#), Banking University of Ho Chi Minh City, Viet Nam
[Dr. Riza Mubida](#), University of Bandar Lampung, Indonesia
[Dr. Jitendra Mohan](#), Jaypee Institute of Information Technology, India
[Dr. Ebrahim Mattar](#), University of Bahrain, Bahrain
[Dr. Pradeep Kumar](#), University of Kwazulu-Natal, South Africa
[Dr. Taichen Chen](#), National Central University Taiwan, Taiwan, Province of China
[Prof. Viranjay Mohan Srivastava](#), University of KwaZulu-Natal, South Africa
[Dr. Pavan Kumar Y. V.](#), Vellore Institute of Technology - Andhra Pradesh (VIT-AP) University, India
[Prof. Liza Abdul Latiff](#), Universiti Teknologi Malaysia, Malaysia
[Dr. Zairi Ismael Rizman](#), Universiti Teknologi MARA, Malaysia
[Dr. Zaid Abdi Alkareem Alyasseri](#), University of Kufa, Iraq
[Dr. Reghunadhan Rajesh](#), Central University of Kerala, India
[Dr. Dimitri Papadimitriou](#), University of Antwerp - imec, Belgium
[Dr. Danilo Avola](#), Università degli Studi di Roma La Sapienza, Italy
[Prof. Dr. Eros Pasero](#), Politecnico di Torino, Italy
[Dr. Abdalhossein Rezaei](#), ACECR, Iran, Islamic Republic of
[Dr. Karthikeyan Ramasamy](#), M.Kumarasamy College of Engineering, Karur, TamilNadu, India., India
[Dr. Kennedy O. Okokpulle](#), Covenant University, Nigeria
[Dr. Syed Manzoor Qasim](#), King Abdulaziz City for Science and Technology, Saudi Arabia
[Dr. Sébastien Lallechère](#), Université Clermont Auvergne, France
[Prof. Mohammed I. Alghamdi](#), Al-Baha University, Saudi Arabia
[Prof. Dr. Eric Renault](#), UGM, Université Gustave Eiffel, CNRS, ESIEE Paris, France
[Prof. Dr. Leo P. Ligthart](#), Delft University of Technology, Netherlands
[Prof. Dr. Mohammad Faiz Liew Bin Abdullah](#), Universiti Tun Hussein Onn Malaysia, Malaysia
[Prof. Ming-Fong Tsai](#), National United University, Taiwan, Province of China
[Prof. Dr. Yongmin Zhang](#), Central South University, China
[Prof. Dimitrios Chrysostomou](#), Aalborg University, Denmark
[Prof. Young-Long Chen](#), National Taichung University of Science and Technology, Taiwan
[Dr. Carlo Massaroni](#), Università Campus Bio-Medico di Roma, Italy
[Dr. Muhammad Zeeshan Shakir](#), University of the West of Scotland, United Kingdom
[Dr. Min Keng Tan](#), Universiti Malaysia Sabah, Malaysia
[Dr. Chrysovalantou Zlogou](#), Centre for Research and Technology Hellas, Greece
[Dr. Nuri Yilmazer](#), Texas A&M University-Kingsville, United States
[Dr. Quoc-Tuan Vien](#), Middlesex University, United Kingdom
[Dr. Vasco N. G. J. Soares](#), Polytechnic Institute of Castelo Branco, Instituto de Telecomunicações, Portugal
[Dr. Ashkan Sami](#), Shiraz University, Iran, Islamic Republic of
[Dr. Ahmed Toaha Mobashsher](#), The University of Queensland, Australia
[Dr. Md Jan Nordin](#), Universiti Kebangsaan Malaysia, Malaysia
[Dr. Nafarizal Nayan](#), Universiti Tun Hussein Onn Malaysia, Malaysia
[Dr. Mohd Yusoff Mashor](#), Universiti Malaysia Perlis (UNIMAP), Malaysia
[Alireza Ghasempour](#), University of Applied Science and Technology, United States
[Dr. Haikal El Abed](#), Technical Trainers College (TTC), Saudi Arabia
[Dr. Dinh-Thuan Do](#), Wireless Communications Research Group, Ton Duc Thang University, Viet Nam
[Prof. Ahmed El Quaikadi](#), Abdelmalek Essaadi University, Morocco
[Dr. Hanikumar Rajaguru](#), Bannari Amman Institute of Technology, India
[Dr. Nuno Rodrigues](#), Instituto Politécnico de Bragança, Portugal
[Dr. Marco Pellegrini](#), LIF Srl, Italy
[Prof. Carlos Machado Ferreira](#), Instituto Superior de Engenharia de Coimbra, Portugal
[Prof. Felix J. Garcia Clemente](#), University of Murcia, Spain
[Prof. Dr. Hussain Al-Ahmad](#), University of Dubai, United Arab Emirates
[Prof. Chao Hsien Lee](#), National Taipei University of Technology, Taiwan
[Prof. Dr. Mirosław Swiercz](#), Politechnika Białostocka, Poland
[Prof. Dr. Media Anugerah Ayu](#), Sampoerna University, Indonesia
[Prof. Dr. Omar Lengerke](#), Universidad Autónoma de Bucaramanga, Colombia
[Prof. Dr. Srinivasan Alayandar](#), CK College of Engineering and Technology, India
[Assoc. Prof. Dr. LUNCHAKORN Wuttisittikuljij](#), Chulalongkorn University, Thailand
[Assoc. Prof. Dr. Mochammad Facta](#), Diponegoro University, Indonesia
[Assoc. Prof. Dr. Mohamed Arezki Mellal](#), M'Hamed Bougara University, Algeria
[Assoc. Prof. Dr. Naziha Ahmad Azli](#), Universiti Teknologi Malaysia, Malaysia
[Asst. Prof. Dr. Supavadee Aramvith](#), Chulalongkorn University, Thailand
[Dr. Achmad Widodo](#), Universitas Diponegoro, Indonesia
[Dr. Sandeep Saxena](#), Galgotias College of Engineering and Technology Greater Noida (U.P), India
[Asst. Prof. Dr. Mohammed I. Younis](#), University of Baghdad, Iraq
[Dr. Azian Azamimi Abdullah](#), Universiti Malaysia Perlis, Malaysia
[Dr. Ahmed Elmisery](#), University of South Wales, United Kingdom
[Dr. Maria Chiara Caschera](#), CNR IRPPS, Italy
[Dr. Azura Che Soh](#), Universiti Putra Malaysia, Malaysia
[Dr. José Alfredo Ferreira Costa](#), Universidade Federal do Rio Grande do Norte, Brazil
[Dr. Tianhua Xu](#), University of Warwick, United Kingdom
[Dr. Petru Adrian Costas](#), Transilvania University of Brasov, Romania
[Dr. Sorin Ioan Deaconu](#), Politechnica University Timisoara, Romania
[Dr. Deris Stiawan](#), Universitas Sriwijaya, Indonesia
[Dr. Ke-Lin Du](#), Concordia University, Canada
[Dr. Farhan Aadil](#), COMSATS Institute of Information and Technology, Pakistan
[Dr. Vicente García Díaz](#), University of Oviedo, Spain
[Dr. Mihai Gavrilas](#), Technical University of Iasi, Romania
[Dr. Abdelfatteh Haidine](#), ENSA El Jadida - University Chouaib Doukkali, Morocco
[Dr. Hazura Haroon](#), Universiti Teknikal Malaysia Melaka, Malaysia
[Dr. Jacek Stando](#), Technical University of Lodz, Poland
[Dr. Nisheeth Joshi](#), Banasthali University, India
[Dr. Jakov S. Korovin](#), Southern Federal University, Russian Federation
[Dr. Karl R. P. H. Leung](#), Hong Kong Institute of Vocational Education, Hong Kong
[Dr. Luca Di Nunzio](#), University of Rome Tor Vergata
[Dr. Munawar A Riyadi](#), Universitas Diponegoro, Indonesia
[Dr. Rostam Affendi Hamzah](#), Universiti Teknikal Malaysia Melaka, Malaysia
[Dr. Youssef Said](#), Tunisie Telecom Sys'Com Lab, National Engineering School of Tunis (ENIT), Tunisia

TELKOMNIKA Telecommunication, Computing, Electronics and Control
ISSN: 1693-6930, e-ISSN: 2302-9293
Universitas Ahmad Dahlan, 4th Campus
Jl. Ringroad Selatan, Kragilan, Tamanan, Banguntapan, Bantul, Yogyakarta, Indonesia 55191
Phone: +62 (274) 563515, 511830, 379418, 371120 ext. 4902, Fax: +62 274 564604

02352257

[View TELKOMNIKA Stats](#)



HOME ABOUT LOGIN REGISTER SEARCH CURRENT ARCHIVES ANNOUNCEMENTS

Home > Archives > **Vol 16, No 6**

Vol 16, No 6

December 2018

DOI: <http://dx.doi.org/10.12928/telkomnika.v16i6>

Table of Contents

A Novel Structure of a Wideband Zero-Bias Power Limiter for ISM Band	PDF
<i>Khalifa Echchakhaoui, Elhassane Abdelmounim, Jamal Zbitou, Hamid Bennis, Ahmed Errkik, Angel Mediavilla Sanchez</i>	2481-2491
Design and Analysis of Broadband Elliptical Microstrip Patch Antenna for Wireless Communication	PDF
<i>Ali Khalid Jassim, Raad H. Thaher</i>	2492-2499
Optimization a Scheduling Algorithm of CA in LTE ADV	PDF
<i>Sarmad K. Ibrahim, Nasser N. Khamiss</i>	2514-2521
Performance Evaluation of Low-Cost GPS Time Server Based on NTP	PDF
<i>Heri Andrianto, Yohana Susanthi, Denny Suryadi</i>	2528-2535
Hybrid Filter Scheme for Optimizing Indoor Mobile Cooperative Tracking System	PDF
<i>Rafina Destianti Ainul, Prima Kristalina, Amang Sudarsono</i>	2536-2548
A Compact Reconfigurable Dual Band-Notched Ultra-Wideband Antenna using Varactor Diodes	PDF
<i>Sam Weng Yik, Zahriladha Zakaria, Herwansyah Lago, Noor Azwan Shairi</i>	2557-2562
RS Codes for Downlink LTE System over LTE-MIMO Channel	PDF
<i>Ghasan Ali Hussain, Lukman Audah</i>	2563-2569
A Two-stages Microstrip Power Amplifier for WiMAX Applications	PDF
<i>Amine Rachakh, Larbi El Abdellaoui, Jamal Zbitou, Ahmed Errkik, Abdelali Tajmouati, Mohamed Latrach</i>	2500-2506
Electromagnetic Characteristics Measurement of Organic Material Absorber	PDF
<i>Reza Septiawan, Sardjono Trihatmo, Juliati Junde, Dody A. Winarto, Arief Rufiyanto, Erik Madyo Putro, Budi Sulisty, Arky Astasari</i>	2507-2513
Loss Quantization of Reflectarray Antenna Based on Organic Substrate Materials	PDF
<i>H. I Malik, M. Y Ismail, Sharmiza Adnan, S. R Masrol</i>	2570-2577
Comparison of Raindrop Size Distribution Characteristics Across the Southeast Asia Region	PDF
<i>Manhal Alhilali, Lam Hong Yin, Jafri Din</i>	2522-2527
Proposed Model for Interference Estimation in Code Division Multiple Access	PDF
<i>Dalal Kanaan Taher, Adheed Hassan Sallomi</i>	2549-2556
Multiuser Detection with Decision-Feedback Detectors and PIC in MC-CDMA System	PDF
<i>Leila Sahraoui, Djemil Messadeg, Saliha e Hariz, Nouredine Doghmane</i>	2578-2587
Different Multilayer Substrate Approaches to Improve Array Antenna Characteristics for Radar Applications	PDF
<i>N. Chater, T. Mazri, M. Benbrahim</i>	2588-2596
Analysis Predicted Location of Harmonic Distortion in RF Upconverter Structure	PDF
<i>Sirmayanti Sirmayanti, Mike Faulkner</i>	2608-2615
Performance Enhancement of Wideband Reflectarray Antennas Embedded on Paper Substrate Materials	PDF
<i>M. Y. Ismail, H. I. Malik</i>	2616-2621
Proposed P-shaped Microstrip Antenna Array for Wireless Communication Applications	PDF
<i>Raad H. Thaher, Noor Baqir Hassan</i>	2597-2607
Underwater Image De-noising using Discrete Wavelet Transform and Pre-Whitening Filter	PDF
<i>Mohanad Najim Abdulwahed, Ali Kamil Ahmed</i>	2622-2629
Implementation of Integration VaaMSN and SEMAR for Wide Coverage Air Quality Monitoring	PDF
<i>Yohanes Yohanie Fridelin Panduman, Adnan Rachmat Anom Besari, Sritrasta Sukaridhoto, Rizqi Putri Nourma Budiarti, Rahardhita Widyatra Sudibyo, Funabiki Nobuo</i>	2630-2642
Secure Code Generation for Multi-Level Mutual Authentication	PDF
<i>Gregor Alexander Aramice, Jaafar Qassim Kadhim</i>	2643-2650
Modified DCT-based Audio Watermarking Optimization using Genetics Algorithm	PDF

USER
 Username:
 Password:
☐ Remember me

TEMPLATE
TELKOMNIKA TEMPLATE

ONLINE SUBMISSION

QUICK LINKS

- + Author guideline
- + Editorial Boards
- + Reviewers
- + Online Submissions
- + Abstracting and Indexing
- + Copyright and Licensing
- + Publication Ethics
- + Visitor Statistics
- + Contact Us

JOURNAL CONTENT
 Search:
 Search Scope:

 Browse:

- + By Issue
- + By Author
- + By Title
- + Other Journals

<i>Ledy Novamizanti, Gelar Budiman, Irma Safitri</i>	2651-2660
Numerical Method for Evaluating E-Cash Security	PDF
<i>Dany Eka Saputra, Sarwono Sutikno, Suhono Harso Supangkat</i>	2668-2675
Statistical Tuning Chart for Mapping Porosity Thickness: a Case Study of Channel Sand Bodies in the Kutei Basin Reservoir	PDF
<i>Abdul Haris, Agus Riyanto, Sri Mardiyati</i>	2676-2682
Repair and Replacement Strategy for Optimizing Cost and Time of Warranty Process using Integer Programming	PDF
<i>Ardy Januanto, Riyanarto Sarno</i>	2683-2691
Determining Strategies on Playing Badminton using the Knuth-Morris-Pratt Algorithm	PDF
<i>Lala Septem Riza, Muhammad Irfan Firmansyah, Herbert Siregar, Dian Budiana, Alejandro Rosales-Pérez</i>	2763-2770
Towards Adaptive Sensor-cloud for Internet of Things	PDF
<i>I Made Murwantara, Hendra Tjahyadi, Pujianto Yugopuspito, Arnold Aribowo, Irene A. Lazarusli</i>	2771-2781
Design Mobile App for Increase the Visitor Museum using Gamification Method	PDF
<i>Novian Adi Prasetyo, Suyoto Suyoto</i>	2791-2798
A New Framework for Information System Development on Instant Messaging for Low Cost Solution	PDF
<i>I Made Sukarsa, I Ketut Gede Darma Putra, Nyoman Putra Sastra, Lie Jasa</i>	2799-2808
Using Alpha-cuts and Constraint Exploration Approach on Quadratic Programming Problem	PDF
<i>Yosza Dasril, Zahrladha Zakaria, Ismail Bin Mohd</i>	2782-2790
Message Oriented Middleware For Library's Metadata Exchange	PDF
<i>Ni Wayan Wisswani, I Wayan Kandi Wijaya</i>	2756-2762
Fuzzy Rule-based Classification Systems for the Gender Prediction from Handwriting	PDF
<i>Lala Septem Riza, Aldi Zainaffif, Rasim Rasim, Shah Nazir</i>	2725-2732
Speech Recognition Application for the Speech Impaired using the Android-based Google Cloud Speech API	PDF
<i>Nenny Anggraini, Angga Kurniawan, Luh Kesuma Wardhani, Nashrul Hakiem</i>	2733-2739
Integrated Analytical Hierarchy Process and Objective Matrix in Balanced Scorecard Dashboard Model for Performance Measurement	PDF
<i>Okfalisa Okfalisa, Septia Anugrah, Wresni Anggraini, Muhammad Absor, S.S.M. Fauzi, Saktioto Saktioto</i>	2703-2711
Reinforced Island Model Genetic Algorithm to Solve University Course Timetabling	PDF
<i>Alfian Akbar Gozali, Shigeru Fujimura</i>	2747-2755
The Readiness of Palm Oil Industry in Enterprise Resource Planning	PDF
<i>Darius Antoni, Deni Fikari, Muhamad Akbar, Ferry Jie</i>	2692-2702
A Review of Energy-aware Cloud Computing Surveys	PDF
<i>Azlan Ismail, Nor Adzlan Jamaludin, Suzana Zambri</i>	2740-2746
Thermodynamic Performance and Wave Propagation Sensor System of Fiber Bragg Grating in Liquid Media	PDF
<i>Romi F. Syahputra, Ridho Kurniawan, Yunita I. Lubis, Mesra Sania, Okfalisa Okfalisa, Saktioto Saktioto</i>	2661-2667
Image Analysis using Color Co-occurrence Matrix Textural Features for Predicting Nitrogen Content in Spinach	PDF
<i>Yusuf Hendrawan, Indah Mustika Sakti, Yusuf Wibisono, Muchnuria Rachmawati, Sandra Malin Sutan</i>	2712-2724
Assessment of Internet Banking Services Continued Use: Role of Socio-Cognitive and Relational View	PDF
<i>Mira Kartiwi, Ali Rfieda</i>	2817-2827
Anomaly Detection based on Control-flow Pattern of Parallel Business Processes	PDF
<i>Hendra Darmawan, Riyanarto Sarno, Adhatus Solichah Ahmadiyah, Kelly Rossa Sungkono, Cahyaningtyas Sekar Wahyuni</i>	2809-2816
Development of a Modular Unit of a Higher Level Framework or Tool for Basic Programming Course Teaching Through E-Learning Mode	PDF
<i>Radhika Pathi, G.V. Rao, P. Rama Krishna, P. Bharath Kumar</i>	2828-2834
Stochastic Computing Correlation Utilization in Convolutional Neural Network Basic Functions	PDF
<i>Hamdan Abdellatef, Mohamed Khalil Hani, Nasir Shaikh Husin, Sayed Omid Ayat</i>	2835-2843
Design of Dual Band Microstrip Antenna for Wi-Fi and WiMax Applications	PDF
<i>Raad H. Thaher, Zainab S. Jamil</i>	2864-2870
An Adaptive Internal Model for Load Frequency Control Using Extreme Learning Machine	PDF
<i>Adelhard Beni Rehiara, He Chongkai, Yutaka Sasaki, Naoto Yorino, Yoshifumi Zoka</i>	2879-2887
Sub-1 GHz Wireless Nodes Performance Evaluation for Intelligent Greenhouse System	PDF
<i>I Nyoman Kusuma Wardana, Ngakan Nyoman Kutha Krisnawijaya, I Wayan Aditya Suranata</i>	2888-2895
Voltage Regulation of Boost Converter using Observer based Sliding Mode Controller	PDF
<i>Ramadhani Kurniawan Subroto, Sapriesty Nainy Sari, Zainul Abidin, Kuo Lung Lian</i>	2896-2904
Application of EMG and Force Signals of Elbow Joint on Robot-assisted Arm Training	PDF

<i>Riky Tri Yunardi, Eva Inayah Agustin, Risalatul Latifah, Winarno Winarno</i>	2913-2920
Performance Evaluation of Centralized Reconfigurable Transmitting Power Scheme in Wireless Network-on-chip	PDF
<i>M. S. Rusli, A. A. H. Ab Rahman, U. U. Sheikh, N. Shaikh Husin, Michael L. P. Tan, T. Andromeda, M. N. Marsono</i>	2844-2854
Radial Derivative and Radial Inversion for Interpreting 4D Gravity Anomaly Due to Fluids Injection Around Reservoir	PDF
<i>Muhammad Zuhdi, Sismanto Sismanto, Ari Setiawan, Jarot Setyowiyoto, Adi Susilo, Muhammad Sarkowi</i>	2855-2863
The Application of General MOS Gas Sensors for Discriminating Formalin Content	PDF
<i>Arief Sudarmaji, Budi Gunawan, Shoufika Hilyana, Henry Fernando, Agus Margiwiyatno</i>	2905-2912
A Small RLSA Antenna Utilizing the Specification of Back Fires 17 dBi LAN Antennas	PDF
<i>Teddy Purnamirza, Prayoga Budikesuma, Imran M. Bin Ibrahim, Depriwana Rahmi, Rika Susanti</i>	2871-2878
Low-Cost Fiber Optic Chemical Sensor Development for Fishpond Application	PDF
<i>Budi Mulyanti, Yuki Maolid Rizki Faozan, Ajuni B. Pantjawi, Roer Eka Pawinanto, Lilik Hasanah, Wahyu Sasongko Putro</i>	2921-2929
Sensorless Control of a Fault-Tolerant Multi-Level PMSM Drive	PDF
<i>Kamel Saleh, Mark Sumner</i>	2930-2942
Modified SEPIC Converter Performance for Grid-connected PV Systems under Various Conditions	PDF
<i>Rizky Ajie Aprilianto, Subiyanto Subiyanto, Tole Sutikno</i>	2943-2953
Bank of Extended Kalman Filters for Faults Diagnosis in Wind Turbine Doubly Fed Induction Generator	PDF
<i>Imane Idrissi, Houcine Chafouk, Rachid El Bachtiri, Maha Khanfara</i>	2954-2966
Transient Power Quality Performance of Multi Photovoltaics using MPPT P and O/MPPT Fuzzy	PDF
<i>Amirullah Amirullah, Agus Kiswantono, Ontoseno Penangsang, Adi Soeprijanto</i>	2967-2979
Developing Fuzzy Inference System of the Observed Albireo Star's Trail using Surface Meteorological Parameter over ITERA Astronomical Observatory (IAO)	PDF
<i>Wahyu Sasongko Putro, Wirid Birastru, Robiatul Muztaba, Anissa Novia Indra Putri, Nindhita Pratiwi, Hakim Luthfi Malasan</i>	2980-2987
Solar Panel Control System Using an Intelligent Control: T2FSMC and Firefly Algorithm	PDF
<i>Mardlijah Mardlijah, Zainullah Zuhri</i>	2988-2998
Particle Filter with Integrated Multiple Features for Object Detection and Tracking	PDF
<i>Muhammad Attamimi, Takayuki Nagai, Djoko Purwanto</i>	3008-3015
Optimal Control for Torpedo Motion based on Fuzzy-PSO Advantage Technical	PDF
<i>Viet Dung Do, Xuan Kien Dang</i>	2999-3007
Inclined Image Recognition for Aerial Mapping using Deep Learning and Tree based Models	PDF
<i>Muhammad Attamimi, Ronny Mardiyanto, Astria Nur Irfansyah</i>	3034-3044
PID Control Design for Biofuel Furnace using Arduino	PDF
<i>Agus Budianto, Wahyu S. Pambudi, Sumari Sumari, Andik Yulianto</i>	3016-3023
Transfer Function, Stabilizability, and Detectability of Non-autonomous Riesz-spectral Systems	PDF
<i>Sutrima Sutrima, Christiana Rini Indrati, Lina Aryati</i>	3024-3033

TELKOMNIKA Telecommunication, Computing, Electronics and Control

ISSN: 1693-6930, e-ISSN: 2302-9293

Universitas Ahmad Dahlan, 4th Campus

Jl. Ringroad Selatan, Kragilan, Tamanan, Banguntapan, Bantul, Yogyakarta, Indonesia 55191

Phone: +62 (274) 563515, 511830, 379418, 371120 ext. 4902, Fax: +62 274 564604

02352288[View TELKOMNIKA Stats](#)

An Adaptive Internal Model for Load Frequency Control using Extreme Learning Machine

Adelhard Beni Rehiara^{*1}, He Chongkai², Yutaka Sasaki³, Naoto Yorino⁴, Yoshifumi Zoka⁵

^{1,2,3,4,5}Graduate School of Engineering, Hiroshima University Higashi-Hiroshima, Japan

¹Electrical Engineering, University of Papua Manokwari, Indonesia

^{*}Corresponding author, e-mail: ab-rehiara@hiroshima-u.ac.jp

Abstract

As an important part of a power system, a load frequency control has to be prepared with a better controller to ensure internal frequency stability. In this paper, an Internal Model Control (IMC) scheme for a Load Frequency Control (LFC) with an adaptive internal model is proposed. The effectiveness of the IMC control has been tested in a three area power system. Results of the simulation show that the proposed IMC with Extreme Learning Machine (ELM) based adaptive model can accurately cover the power system dynamics. Furthermore, the proposed controller can effectively reduce the frequency and mechanical power deviation under disturbances of the power system.

Keywords: IMC, MPC, ELM, LFC, power system.

Copyright © 2018 Universitas Ahmad Dahlan. All rights reserved.

1. Introduction

In the power system operation, deviation of frequency would be a critical issues since the deviation could cause many troubles to devices connected to the power system. It is reported that the frequency change will affect operation and speed control of both synchronous and asynchronous motors, increase reactive power consumption and furthermore degrade load performance, overload transmission lines, and finally interfere system protection. An LFC is a main part of a power system to minimize frequency variation by maintaining power exchange between power system areas. Some works have been done in the area of LFC [1-9], including [1] designed a model predictive control (MPC) based LFC for a multi-area power system considering wind turbines operation, [2] compare MPC and PI performance against a conventional AGC system, [3] presented fuzzy controller for LFC of three area power system and recently [4] discussed a new LFC method for multi-area power system.

Internal Model Control (IMC) is a well-established control structure and it is widely applied in process control applications. An IMC incorporates a plant model into its structure as an internal model so that the controller output will be based on the difference between internal model and plant output. Morari in [10] has proved that the controller has dual stability, zero offset, and perfect control properties. Since plant models are mostly linearized models, it is almost impossible for an IMC to be a perfect control. An adaptive model will be a solution to be close to the "perfect control" since it can be updated in a certain time to do corrections for the existing model. Many previous researches have succeeded to apply the adaptive model into a controller i.e. PI/PID [10-13], Fuzzy controller [14], or MPC [15].

Since introduced a decade before, extreme learning machine (ELM) has been used in many cases and applications. It has accurate predictions in short time training compared to its ancestor which is a feed-forward neural network. An adaptive internal model has been introduced in [7] using prediction error minimization (PEM) algorithm. Due to time-consuming, this method is not appropriated to be used in an online application. Therefore, an ELM with its features is a good candidate to replace the PEM method. In this paper, an ELM based adaptive IMC controller is built by employing an internal model in an adaptive scheme and an MPC as the main controller to control a load frequency of a power system.

2. Research Method

2.1. Model Predictive Control

MPC is an advanced control method that used a plant model to predict the optimal movement of the plant. A Laguerre based MPC would be a solution for online computation compare to classical MPC [16, 17]. In addition, a Laguerre based MPC can increase the feasible region of the optimization problem [16]. Accurate approximation of control signal Δu may need many parameters that cause poor numerical solutions and heavy computational load when classical MPC is implemented in rapid sampling, complicated process dynamics and/or high demand on closed-loop performance [16, 17].

The discrete Laguerre function is transformed from its original using invert z-transformation as shown in (1). The Laguerre function vector and initial condition shown in (2) and (3) respectively [6, 8, 17].

$$\Gamma_N(z) = \frac{\sqrt{1-a^2}}{1-az^{-1}} \left(\frac{z^{-1}-a}{1-az^{-1}} \right)^{N-1} \quad (1)$$

$$L(k+1) = A_l L(k) \quad (2)$$

$$L(0)^T = \sqrt{\alpha} \begin{bmatrix} 1-a & a^2-a^3 & \dots & (-1)^{N-1} a^{N-1} \end{bmatrix}^T \quad (3)$$

Minimization of output errors for m sampling instant is done by taking a minimal solution of an objective function J as in (4). Closed loop feedback control with optimal gain K_{mpc} (6) is formulated in (5) and receding horizon control law is realized in (7).

$$J = \sum_{m=1}^{Np} x(k+m|k)^T Q x(k+m|k) + \eta^T R \eta \quad (4)$$

$$x(k+1) = (A - BK_{mpc})x(k) \quad (5)$$

$$K_{mpc} = L(0)^T \Omega^{-1} \Psi \quad (6)$$

$$\Delta u = -K_{mpc} x \quad (7)$$

where,

$$A_l = \begin{bmatrix} a & 0 & 0 & 0 & \dots & 0 \\ \alpha & a & 0 & 0 & \dots & 0 \\ -a\alpha & \alpha & a & 0 & \dots & 0 \\ a^2\alpha & -a\alpha & \alpha & a & \dots & 0 \\ \vdots & \vdots & \vdots & \vdots & \ddots & \vdots \\ -a^{N-2}\alpha & -a^{N-3}\alpha & -a^{N-4}\alpha & \dots & -a^{N-N}\alpha & a \end{bmatrix}$$

$$\eta = \Omega^{-1} \Psi$$

$$\Omega = \sum_{m=1}^{Np} \phi(m) Q \phi(m)^T + R_L$$

$$\Psi = \sum_{m=1}^{Np} \phi(m) Q A^m$$

The parameters of N , a , A_l and L are the length of Laguerre network, time scaling factor, a Toeplitz matrix with $\alpha = (1-a^2)$, and Laguerre function's state vector respectively. The matrices of $Q \in \mathbb{R}^{ns \times ns}$ and $R \in \mathbb{R}^{ni \times ni}$ are weighting matrices, $\eta \in \mathbb{R}^{ns \times N}$ is the parameter vector of N Laguerre function and ϕ is a Hessian matrix. N_p is the number of prediction horizon and Δu is a vector of the control parameter.

2.2. Internal Model Control

An internal model that placed into a normal closed-loop control system, including controller, plant and/or sensor, may perform Internal Model Control systems as shown in Figure1. The difference between signal correction \dot{r} and set-point r is the command to the controller to signal u to the plant. Control law applied for the IMC control can be written as follows [18].

$$y = PQr + (1 - GQ)d_m \quad (8)$$

$$u = Qr - Qd_m \quad (9)$$

$$e = (1 - PQ)r - (1 - GQ)d_m \quad (10)$$

The difference between IMC and the classical controller is that an IMC will correct the actual output before it is fed back. An IMC can use the internal model to predict the future output of the plant and also to make correction of the output. It can also work with another controller to control a plant [10], to tune other controller [19], or to combine with the other controller such as PI/PID [13, 18-22], Fuzzy controller [14, 23], Neural Network [24] or MPC [15, 24, 25].

An adaptive IMC controller refers to a model and/or controller that can be updated in a certain time. By tuning a proper gain to the model and/or controller following the disturbance, the controller can be adaptive to the disturbance. In order to perform adaptive scheme of an IMC, another block for system identification should be presented inside the IMC structure as appeared in the dotted block of Figure1.




Figure 1. IMC principle

2.3. Extreme Learning Machine

An ELM is basically a single hidden layer feed-forward neural network (SLFN) which has an excellent training algorithm. Input weight and hidden layer biases are not necessarily adjusted and those can be chosen arbitrarily in this algorithm. Then the output weight of the SLFNs can be determined by a generalized inverse operation of the hidden layer output matrices. In fact, this procedure has been fastening this algorithm.

For a given \tilde{n} training set samples (x_j, t_j) where $x_j = [x_{j1}, x_{j2}, \dots, x_{j\tilde{n}}]^T$ and $t_j = [t_{j1}, t_{j2}, \dots, t_{j\tilde{n}}]^T$, an SLFN with \tilde{N} hidden neurons and activation function $g(x)$ is expressed as [26, 27]

$$\sum_{i=1}^{\tilde{N}} \beta'_i g(x_j) = \sum_{i=1}^{\tilde{N}} \beta'_i g(w_i x_j + b_i) = o_j, j = 1, 2, \dots, \tilde{n} \quad (11)$$

where $w_i = [w_{i1}, w_{i2}, \dots, w_{i\tilde{n}}]^T$, $\beta'_i = [\beta'_{i1}, \beta'_{i2}, \dots, \beta'_{i\tilde{n}}]^T$, b_i , and o_j are the connecting weight of i^{th} hidden neuron to input neuron, the connecting weights of the i^{th} hidden neuron to the output neurons, the bias of the i^{th} hidden node, and the actual network output with respect to input x_j respectively. Because the standard SLFN can minimize the error between t_j and o_j , (11) can be rewritten as follows.

$$\sum_{i=1}^{\tilde{N}} \beta'_i g(w_i x_j + b_i) = t_j, j = 1, 2, \dots, \tilde{n} \quad (12)$$

In simple (12) can be $H\beta' = T$ so that the output weight matrix β' can be solved by least square solution as in (13).

$$\beta' = H^+ T \quad (13)$$

The hidden layer output matrix H and the network output T are formulated as follows.

$$H(w_i, b_i) = \begin{bmatrix} g(w_1 x_1 + b_1) & \cdots & g(w_{\tilde{N}} x_1 + b_{\tilde{N}}) \\ \vdots & \cdots & \vdots \\ g(w_1 x_{\tilde{n}} + b_1) & \cdots & g(w_{\tilde{N}} x_{\tilde{n}} + b_{\tilde{N}}) \end{bmatrix}, \text{ and } T = \begin{bmatrix} t_1^T \\ \vdots \\ t_{\tilde{n}}^T \end{bmatrix} \quad (14)$$

2.4. Proposed Controller

As proposed in this research, an adaptive model will be used to provide an updated model of the plant. The adaptive model is generated by using a classification based extreme learning machine (ELM) algorithm by utilizing input and output data. The proposed controller uses MPC controller as its main controller combining with an adaptive ELM model as the internal model. The complete block diagram of the proposed controller is shown in Figure 2. The ELM model was trained using controller output Δu and frequency deviation Δf as input and output data respectively. After trained, the ELM model is used to predict frequency deviation Δf for a given controller signal Δu . The algorithm for simulation is written in Algorithm 1.

Algorithm 1 : Adaptive IMC

1. set disturbances and noises
2. configure ELM model
3. for $j=1$ to simulation time
4. \vdots
5. for $i=1$ to n-area
6. calculate Δu
7. update state matrix $\Delta \hat{x}_i$
8. train ELM model
9. predict ELM output Δy_{mi}
10. calculate $\Delta \dot{y}_i = \Delta y_i - \Delta y_{mi}$
11. \vdots
12. end
13. end




Figure 2. Proposed Adaptive IMC Scheme

2.5. Power system model

A model of power system dynamics can be redrawn in Figure 3. The frequency deviation of the power system, including tie-line power interchange, is expressed as follows.




Figure 3. Power system dynamics

$$\Delta \dot{f}_i = \frac{1}{2H_i} \left(\Delta P_{m,i} - \Delta P_{L,i} - d_i \Delta f_i - \Delta P_{tie,i} \right) \quad (15)$$

The prime mover P_m , governor output P_g , tie-line power interchange P_{tie} are for n areas are formulated in (16-18). Area Control Error (ACE) is chosen as the controller input which is the result of frequency f and tie-line power changes within a control area of the power system defined in (19) [1].

$$\Delta \dot{P}_{m,i} = \left(\frac{1}{T_{g,i}} \right) \Delta P_{g,i} - \left(\frac{1}{T_{t,i}} \right) \Delta P_{m,i} \quad (16)$$

$$\Delta \dot{P}_{g,i} = \frac{1}{T_{g,i}} \left(\Delta P_{C,i} - \frac{\Delta f_i}{R_i} - \Delta P_{g,i} \right) \quad (17)$$

$$\Delta \dot{P}_{tie,i} = 2\pi \left[\sum_{\substack{j=1 \\ j \neq i}}^n T_{ij} \Delta f_i - \sum_{\substack{j=1 \\ j \neq i}}^n T_{ij} \Delta f_j \right] \quad (18)$$

$$ACE_i = \Delta P_{tie,i} + \beta_i \Delta f_i \quad (19)$$

where $P_{L,i}$ is the load/disturbance, $P_{C,i}$ is the controller output, H_i is the equivalent inertia constant, d_i is the damping coefficient, R_i is the speed droop characteristic and β_i is the bias of frequency. T_{ij} is the tie-line synchronizing coefficient between area i and j , $T_{g,i}$ is the governor time constants and $T_{t,i}$ is the turbine time constants of area i .

3. Results and Analysis

3.1. Simulation

The power system configuration for testing the proposed controller is based on [6, 8] with the parameters as shown in Table 1 while the system dynamics are figured in Figure 4. Simulations were done in two cases and the simulation setup is configured in Table 2, where step and random disturbance are imposed on the load in all area. The random disturbance implies load changes of white noise with a maximum 0.1 pu while step disturbance is assumed as load change in constant for a certain time.




Figure 4. Three-area power system configuration

Table 1. Three Area Power System Parameters

Area	d [pu/Hz]	$2H$ [pu s]	R [Hz/pu]	T_g [s]	T_i [s]	\square [pu/Hz]	T_{ij} [pu/Hz]
1	0.015	$\frac{0.166}{7}$	3.00	0.08	0.40	0.3483	$T_{12}=0.20$ $T_{13}=0.25$
2	0.016	$\frac{0.201}{7}$	2.73	0.06	0.44	0.3827	$T_{21}=0.20$ $T_{23}=0.12$
3	0.015	$\frac{0.124}{7}$	2.82	0.07	0.30	0.3692	$T_{31}=0.25$ $T_{32}=0.12$

Table 2. Simulation Setup

Case	Step	Random
	Disturbance [pu]	Disturbance [pu]
I	0.2	0.1
II	0.2	-

A Laguerre function based MPC controller is built to control a three area power system frequency. To ensure the MPC stability, the scaling factor α is tuned to 0.1 while network lengths N is set to 4 for each area controller. The model will be updated each second with the input-output data using ELM method. Overall simulation responses of frequency and mechanical power deviation for both existing and proposed controller are plotted in Figures 5 and 6.

3.2. Discussion

The controller performance is evaluated based on system responses and signal measures. Standard deviation is also provided to indicate how sensitive the controller to response the errors.

For the system responses based evaluation, overshoot and standard deviation are analyzed and the results are provided in Table 3 as well as its visual in Figure 7 and 8 based on system responses in Figure 5 and 6. According to the figures and table, it can be simply known that the proposed controller has very good response overshoot of frequency and mechanical power compared to the existing MPC controller in all areas of both cases. On the other hand, the proposed controller slightly aggressive to the disturbances as shown in high standard deviations in some areas and cases. These are the evidence that the proposed controller can accurately cover the power system dynamics and also it shows the ability to increase controller performance by sending proper feedback to the controller by utilizing the adaptive model.

By the treatment as same as in the case I, the other adaptive internal model for LFC application introduced in [7] has overshoot responses 0.1465, 0.1729, and 0.1652 and standard deviation 0.0294, 0.0443, and 0.0278 for area 1-3 respectively. Compared to the proposed controller, it is proved that the proposed controller has smaller overshoot and higher standard deviation compared. These are the indications that the proposed controller is more active to maintain the frequency change during the simulation and so it only has a small overshoot on the simulation.

Table 3. Frequency and Mechanical Power Deviation Analysis

		Frequency Deviation				Mechanical Power Deviation			
	Area	MPC Cases		Adaptive IMC Cases		MPC Cases		Adaptive IMC Cases	
		I	II	I	II	I	II	I	II
Overshoot	1	0.1346	0.2190	0.0923	0.2047	0.3437	0.3401	0.3080	0.3109
	2	0.0860	0.1162	0.0407	0.1147	0.4164	0.4165	0.3473	0.3484
	3	0.1374	0.2530	0.1259	0.2384	0.4605	0.4625	0.4318	0.4340
Standard Deviation	1	0.1762	0.1967	0.1767	0.1946	0.0372	0.0428	0.0442	0.0814
	2	0.1786	0.1838	0.1795	0.1842	0.0418	0.0432	0.0354	0.0514
	3	0.1714	0.2012	0.1714	0.1976	0.0522	0.0580	0.0450	0.0738




Figure 5. MPC controller responses (a) case i and (b) case II




Figure 6. Adaptive IMC controller responses (a) case i and (b) case ii




Figure 7. Frequency deviation




Figure 8. mechanical power deviation

The signal measured based evaluation of the proposed controller including Integral of the absolute value of the error (IAE), Integral of the square value of the error (ISE) and Integral of the time-weighted absolute value of the error (ITAE) are provided in Table 4. It is shown that the proposed controller has small errors in IAE and ITAE index while it has high deviation in the ISE index in both cases. These are the validation that the proposed controller has no persisting high errors and it adaptively follows the load changes in the simulation.

The specifications of the machine to run the simulation runs are Intel Core i7 2.9 GHz CPU and 16 GB RAM using MatLab 2016a under Windows 10 environment. CPU time for both cases of MPC, and case I and II of adaptive IMC are 1.5509, 1.5446, 6.6927 and 6.4599 seconds respectively. It seems like the proposed controller will need time 4 times longer than the existing controller since it needs to build its own model in a certain period which is in this cases every second. This may not degrade the performance in real operation since the CPU time is still littler than simulation setting time.

Table 4. Controller Index Analysis

	Area	MPC			Adaptive IMC		
		IAE	ISE	ITAE	IAE	ISE	ITAE
Case I	1	1.9340	0.6858	10.6362	1.9039	0.6900	10.1068
	2	1.6508	0.7028	6.9319	1.6532	0.7118	6.8517
	3	2.1407	0.6593	14.1713	2.0966	0.6589	13.4449
	avg	1.9085	0.6827	10.5798	1.8846	0.6869	10.1345
Case II	1	2.2608	0.7425	15.0622	2.2289	0.7444	14.4818
	2	1.6748	0.7204	6.8818	1.6792	0.7297	6.8696
	3	2.6418	0.7685	20.5055	2.5884	0.7626	19.6189
	avg	2.1924	0.7438	14.1498	2.1655	0.7456	13.6567

4. Conclusion

A novel adaptive IMC controller based on ELM method has been introduced in this paper. A three area power system is chosen to validate the controller in handling load frequency control including step and random disturbance. Simulation results show that the proposed controller presents superior responses in all areas of both cases compared to the existing MPC controller.

Acknowledgments

The first author wishes to acknowledge the support of Papua University as well as the Indonesian Ministry of Research, Technology and Higher Education Directorate via General of Higher Education for his study and research in Hiroshima University.

References

- [1] Mohamed TH, Morel J, Bevrani H, Hiyama T. Model predictive based load frequency control-design concerning wind turbines. *Int J Electr Power Energy Syst* [Internet]. 2012;43(1):859–67. Available from: <http://dx.doi.org/10.1016/j.ijepes.2012.06.032>
- [2] Ersdal AM, Imsland L, Uhlen K. Model Predictive Load-Frequency Control. *IEEE Trans Power Syst*. 2016; 31(1) :777–785.
- [3] Jain SK, Bhargava A, Pal RK. *Three area power system load frequency control using fuzzy logic controller*. In: International Conference on Computer, Communication and Control. 2015: 1–6.
- [4] Cai L, He Z, Hu H. A New Load Frequency Control Method of Multi-Area Power System via the Viewpoints of Port-Hamiltonian System and Cascade System. *IEEE Trans Power Syst*. 2017; 32(3): 1689–1700.
- [5] Kumtepli V, Wang Y, Tripathi A. *Multi-area model predictive load frequency control: A decentralized approach*. In: 2016 Asian Conference on Energy, Power and Transportation Electrification, ACEPT 2016. 2017: 25–7.
- [6] Rehiara AB, Sasaki Y, Yorino N, Zoka Y. *A Performance Evaluation of Load Frequency Controller using Discrete Model Predictive Controller*. In: 2016 International Seminar on Intelligent Technology and Its Applications. 2016: 659–64.

- [7] Rehiara AB, Chongkai H, Sasaki Y, Yorino N, Zoka Y. An adaptive IMC-MPC controller for improving LFC performance. In: *2017 IEEE Innovative Smart Grid Technologies - Asia*. Auckland, New Zealand; 2018: 1–6.
- [8] He C, Rehiara AB, Sasaki Y, Yorino N, Zoka Y. *The Application of Laguerre functions based Model Predictive Control on Load Frequency Control*. 24th International Conference on Electrical Engineering. 2018: 1190-1195.
- [9] Abdillah M, Setiadi H, Rehiara AB, Mahmoud K, Farid IW, Soeprijanto A. Optimal selection of LQR parameter using AIS for LFC in a multi-area power system. *J Mechatronics, Electr Power, Veh Technol* [Internet]. 2016; 7(2): 93. Available from: <http://www.mevjournal.com/index.php/mev/article/view/301>
- [10] Qiu Z, Santillo M, Sun J, Jankovic M. *Enhanced composite adaptive IMC for boost pressure control of a turbocharged gasoline engine*. Proc Am Control Conf. 2016; 2016–July(August): 3286–3291.
- [11] Liping F, Xiyang W. *Internal model based iterative learning control for linear motor motion systems*. Proc - ISDA 2006 Sixth Int Conf Intell Syst Des Appl. 2006; 3: 62–6.
- [12] Watanabe, Keiji; Muramatsu E. *Adaptive Internal Model Control of SISO Systems*. In: SICE Annual Conference. Fukui, Japan; 2003: 3084–3089.
- [13] Gu J-J, Shen L, Zhang L-Y. *Application of internal model and self-adaptive PSD controller in the main steam temperature system*. 2005 Int Conf Mach Learn Cybern Icmic 2005. 2005;(August): 570–573.
- [14] Xie WF, Rad AB. Fuzzy adaptive internal model control. *IEEE Trans Ind Electron*. 2000; 47(1): 193–202.
- [15] Milias-Argeitis A, Khammash M. *Adaptive Model Predictive Control of an optogenetic system*. In: 54th IEEE Conference on Decision and Control (CDC). Osaka; 2015: 1265–1270.
- [16] Valencia-Palomo G, Rossiter JA. *Using Laguerre functions to improve efficiency of multi-parametric predictive control*. In: 2010 American Control Conference. USA; 2010: 4731–4736.
- [17] Liuping Wang. *Model Predictive Control System Design and Implementation Using MATLAB*. Springer-Verlag. London; 2009: 103-403.
- [18] Seki H. *Adaptive IMC-PI controllers for process applications*. 12th IEEE Int Conf Control Autom. 2016: 455–460.
- [19] Ho WK, Lee TH, Han HP, Hong Y. Self-tuning IMC-PID control with interval gain and phase margins assignment. *IEEE Trans Control Syst Technol*. 2001; 9(3): 535–541.
- [20] Baba Y, Shigemasa T, Yukitomo M, Kojima F, Takahashi M, Sasamura E. *Model-driven PID control system in single-loop controller*. Proc SICE 2003 Annu Conf. 2003; 1:187–190.
- [21] Shamsuzzoha M, Lee M. *IMC Based Control System Design of PID Cascaded Filter*. SICE-ICASE Int Jt Conf 2006. 2006;Oct. 18(2): 2485–2490.
- [22] Shigemasa T, Yukitomo M, Kuwata R. *A model-driven PID control system and its case studies*. Proc Int Conf Control Appl [Internet]. 2002;1:571–6. Available from: <http://ieeexplore.ieee.org/lpdocs/epic03/wrapper.htm?arnumber=1040248>
- [23] Jin Q, Feng C, Liu M. *Fuzzy IMC for Unstable Systems with Time Delay*. 2008 IEEE Pacific-Asia Work Comput Intell Ind Appl. 2008; 2: 772–778.
- [24] Yan L, Rad AB, Wong YK, Chan HS. *Model based control using artificial neural networks*. In: the 1996 IEEE International Symposium on Intelligent Control. 1996: 283–288.
- [25] Psichogios DC, Ungar LH. *Nonlinear internal model control and model predictive control using neural networks*. In: 5th IEEE International Symposium on Intelligent Control. 1990: 158–163.
- [26] Cao J, Zhang K, Luo M, Yin C, Lai X. Extreme Learning Machine and Adaptive Sparse Representation for Image Classification. *Neural Networks*. 2016; 81(C) :91–102.
- [27] Huang G, Song S, Gupta JND, Wu C. Semi-Supervised and Unsupervised Extreme Learning Machines. *IEEE Trans Cybern*. 2014; 44: 2405–2417.